

INTRODUCTION SCHEDULE

Consumer launch

16th March 2016

EL-SKYPORT UNIVERSAL PLUS SET

The EL-Skyport universal Plus set offers simplicity, durability and reliability. Powered by 2.4 Ghz bandwidth, the transmitter enables speedlights and other flash brand to be triggered by the EL-Skyport system over 16 frequency channels of 4 groups per channel with the range extended to up to 200 m (656').

FEATURES

- Trigger reliably up to 200 m (656 feet) away.
- Hotshoe on the receiver to securely attach speedlights.
- Optimize reception by rotating the transmitter.
- 16 different channels (8 in normal mode and 8 in speed mode) are available.
- Both run on AA batteries, available everywhere.
- Simple to use. All functionalities can be easily adjusted.
- Durable with robust mechanics thanks to their Swiss design.
- Micro-usb socket on the receiver for firmware updates.



EL-Skyport Universal Plus set
19370

Date **15.01.16**

 Bulletin # **10**

SPECIFICATIONS FOR THE TRANSMITTER

Frequency Band	2.4 GHz
Channels	16; (8 in Normal mode – green / 8 in Speed mode – red)
Groups	All and 4: 1, 2, 3, 4
Flash synchronization	Normal: limited to the native X-sync of your camera Speed: for digital medium-format cameras
Range	Up to 200m (656') for triggering
Connection	Foot for camera hotshoe 2.5 mm sync socket
Power source	2x AA batteries
Indicators and Controls	<p>Display Group and frequency channel</p> <p>Buttons On top: group selection, synchronization mode, channel selection, power down, power up and test. On side: on/off.</p>
Compatibility	<p>Channels 1, 3 and 7 are compatible with all enabled EL-Skyport units.</p> <p>Channels 1, 3, 7, 9, 12, 15, 18 and 20 are only compatible with ELC Pro HD and ELB 400.</p>
Dimensions	94.9 x 49.9 x 38.3 mm (3.7" x 2" x 1.5")
Weight	68 g (0.14 lbs.) without batteries

Date **15.01.16**

 Bulletin # **10**

SPECIFICATIONS FOR THE RECEIVER

Frequency Band	2.4 GHz
Channels	16; (8 in Normal mode – green / 8 in Speed mode – red)
Groups	4: 1, 2, 3, 4
Flash synchronization	Normal: limited to the native X-sync of your camera Speed: for digital medium-format cameras
Range	Up to 200m (656') for triggering
Connection	Foot for camera hotshoe 3.5 mm sync socket Micro-usb for firmware updates
Power source	2x AA batteries
Indicators and Controls	Display Group and frequency channel Buttons On left side: channel selection and synchronization mode. On right side: on/off and group selection.
Compatibility	Channels 1, 3 and 7 are only compatible with the previous EL-Skyport transmitter and EL-Skyport transmitter Speed. Channels 1, 3, 7, 9, 12, 15, 18 and 20 are compatible with the EL-Skyport transmitter Plus and EL-Skyport transmitter Plus HS.
Dimensions	93.6 x 49.5 x 41.6 mm (3.7" x 2" x 1.6")
Weight	76 g (0.17 lbs.) without batteries

IN THE BOX

- 1x EL-Skyport transmitter Plus
- 1x 2.5 mm sync cord to PC
- 1x EL-Skyport receiver Plus
- 1x 3.5 mm to 3.5 mm sync cord
- 1x 3.5 mm to 6.35 mm adapter
- 2x Wrist strap
- 1x 2-year warranty